TIP112

Rev. H Oct.-2018

DATA SHEET

WR0553 ṂṂ Ŀ QSQ ᴁṀ ɥ s ǁ ˥

v ˝Ω̣ Parameter	ɬ ᴺ Symbol	˝Ω̣Ӫ Rating	ᴅ Ħ Unit
Collector to Base Voltage	V_{CBO}	100	V
Collector to Emitter Voltage	V_{CEO}	100	V
Emitter to Base Voltage	V_{EBO}	5	V
Collector Current - Continuous	I_C	2	A
Peak Collector Current	I_{CP}	4	A
Base Current - Continuous	I_B	50	mA
Collector Power Dissipation	P_C	[redacted]	[redacted]

[redacted]

[redacted]

/ Electrical Characteristic Curve













/ Package Dimensions



/ Marking Instructions



ب ˝ χ

BR χ	Ѫ ʒ ᴎ Ƞ
TIP112 χ	Ѫ ғ β ʒ ᴺ
---- χ	Ѫ ꟷ ғ ŋ̋ ᴺ Ƞ ı ȩ ꟷ ғ ŋ̋ ᴺ ψ ק

Note:

BR:	Company Code
TIP112:	Product Type.
****:	Lot No. Code, code change with Lot No.